



Gigabit RJ45 y convertidor de fibra SFP MC-1000SFP



Conexión de red extendida

El convertidor de medios MC-1000SFP permite a los usuarios la extensión de la distancia de comunicación con un rendimiento Gigabit a través del cable de fibra óptica. MC-1000SFP proporciona conversión de medios entre 100/1000Base-T y fibra Gigabit a través de varios transceptores.



Convertidor de tamaño compacto

El tamaño compacto de MC-1000SFP tiene un diseño exclusivo con plug-and-play para una fácil instalación y ahorra espacio.

Oficina central



Oficina 1



MC-1000SFP

Oficina 2



MC-1000SFP

Especificaciones

AirLive MC-1000SFP

Estándar <ul style="list-style-type: none"> • IEEE 802.3 10Base-T • IEEE 802.3u 100Base-TX • IEEE 802.3ab 1000Base-T • IEEE 802.3z 1000Base-X 	Adaptador de energía externo <ul style="list-style-type: none"> • 5V / 1A
Puerto <ul style="list-style-type: none"> • 1* 10/100/1000Mbps Gigabit copper port <ul style="list-style-type: none"> - Auto-negotiation, auto-MDI/MDI-X support • 1* 100/1000Mbps Gigabit fiber SFP port <ul style="list-style-type: none"> - SFP supports standard SFP fiber transceiver installation 	Temperatura de funcionamiento <ul style="list-style-type: none"> • 0° ~ 50°C
Buffer de paquete <ul style="list-style-type: none"> • 1 	Jumbo Frame <ul style="list-style-type: none"> • 9k
MAC Address <ul style="list-style-type: none"> • 4K 	Humedad <ul style="list-style-type: none"> • 10% ~ 90% (non-condensing)
	LED <ul style="list-style-type: none"> • PWR (Power) <ul style="list-style-type: none"> - Green - Solid: Power is on - Off: Power is off
	Dimensiones <ul style="list-style-type: none"> • 30 × 110 × 140 mm

Información de pedido:

AirLive MC-1000SFP Gigabit RJ45 and SFP Fiber Converter